

## Appendix II: IVX 128 installer worksheets

### Function 1: System parameters

**Important:** Before programming, make sure you initialize the system!

#### F11 — Initialization

See page D.1 for details.

**F12: Installer**  
Range: 2–8 digits. Default: 789.

**F13: Administrator**  
Range: 2–8 digits. Default: 456.


#### F14 — Set time/date

#### F15 — System timing parameters

See page D.2 for details.

**F151: Flash hook duration**  
Range: 2–20 (0.2–2.0 sec). Default: 15 (1.5 sec).

**F152: Transfer/forward recall timer**  
Range: 1–9 rings. Default: 3.

**F153: Hold/park recall timer**  
Range: 5–960. Default: 60.

**F154: ACD exit timer**  
Range: 0,5–600 (0 = no limit). Default: 180.

**F155: ACD wrap timer**  
Range: 0,5–600 (0 = no limit). Default: 0.

**F156: Cell phone delay**  
Range: 0–50 (0.0–5.0 sec). Default: 10.


#### F16 — Recording alert tone

Options: Enabled, disabled. Default: Disabled.

--

#### F17 — System speed-dial

(Use the worksheet on the following page.)

#### F18 — Serial port baud rate

(SMDR port is fixed at 1200 baud.)

**Maintenance port**  
Options: 300, 1200, 2400, 4800, 9600, 19200, 38400. Default: 38400.

--